


VARISTORS

small silicon carbide disc types for special purposes



These varistors feature low capacitance and are for use in colour television and for protection of aerial inputs of car radios.

Current at 5 V d.c.

≤ 1 mA

Current at 28 V d.c.

≥ 10 mA

W_{\max}

0,1 W

I mA	E V	tolerance on voltage	colour dip code	catalogue number
1	9	$\pm 20\%$	orange	2322 565 90003
1	18	$\pm 12\%$	blue	2322 565 90006